

## Flanged Series(Inch)



select	Inquiry	Size (mm)								Model	Rated load	Rated speed
		d	D	B	B1	rs	Df	Bf	Bf1	Switch	Dust cover type	Cr
3.175	7.938	2.779	3.571	0.1	9.119	0.584	0.787	FR2-5	FR2-5ZZ	558	180	67
3.175	9.525	2.779	3.571	0.2	10.719	0.584	0.787	FR2-6	FR2-6ZZ	640	227	63
3.175	9.525	3.967	3.967	0.3	11.176	0.762	0.762	FR2	FR2ZZ	631	219	67
3.969	7.938	2.779	3.175	0.1	9.119	0.584	0.914	FR155	FR155ZZS	359	150	63
4.762	7.938	2.779	3.175	0.1	9.119	0.584	0.914	FR156	FR156ZZS	359	150	63
4.762	9.525	3.175	3.175	0.1	10.719	0.584	0.787	FR166	FR166ZZ	709	272	60
4.762	12.7	3.969	4.798	0.3	14.351	1.067	1.067	FR3	FR3ZZ	1301	488	53
6.35	9.525	3.175	3.175	0.1	10.719	0.584	0.914	FR168	FR168ZZS	373	172	56
6.35	12.7	3.175	4.762	0.2	13.894	0.584	1.143	FR188	FR188ZZ	1082	442	50
6.35	15.875	4.978	4.978	0.3	17.526	1.067	1.067	FR4	FR4ZZ	1480	621	45
7.938	12.7	3.967	3.967	0.2	13.894	0.787	0.787	FR1810	FR1810ZZS	542	276	48
9.525	22.225	5.558	7.142	0.4	24.613	1.575	1.575	FR6	FR6ZZ	3332	1422	38
12.7	28.575	6.35	7.938	0.4	31.12	1.575	1.575	FR8	FR8ZZ	5108	2413	32
15.875	34.925	7.142	8.733	0.8	38.1	1.745	1.745	FR10	FR10ZZ	5988	3287	25